


**UK Type Examination Certificate CML 21UKEX3645X Issue 0****United Kingdom Conformity Assessment**

- 1 Product or Protective System Intended for use in Potentially Explosive Atmospheres UKSI 2016:1107 (as amended) – Schedule 3A, Part 1
- 2 Equipment **WF-300xxx and WF-250xxx LED Floodlite Luminaire**
- 3 Manufacturer **The Wolf Safety Lamp Co. Limited**
- 4 Address **Saxon Road Works,  
Sheffield, S8 0YA,  
United Kingdom**
- 5 The equipment is specified in the description of this certificate and the documents to which it refers.
- 6 Eurofins E&E CML Limited, Newport Business Park, New Port Road, Ellesmere Port, CH65 4LZ, United Kingdom, Approved Body Number 2503, in accordance with Regulation 43 of the Equipment and Protective Systems Intended for Use in Potentially Explosive Atmospheres Regulations 2016, UKSI 2016:1107 (as amended), certifies that this equipment has been found to comply with the Essential Health and Safety Requirements relating to the design and construction of equipment intended for use in potentially explosive atmospheres given in Schedule 1 of the Regulations.  
The examination and test results are recorded in the confidential reports listed in Section 12.
- 7 If an 'X' suffix appears after the certificate number, it indicates that the equipment is subject to specific conditions of use (affecting correct installation or safe use). These are specified in Section 14.
- 8 This UK Type Examination certificate relates only to the design and construction of the specified equipment. Further requirements of the Regulations apply to the manufacturing process and supply of the product. These are not covered by this certificate.
- 9 Compliance with the Essential Health and Safety Requirements, with the exception of those listed in the confidential report, has been demonstrated through compliance with the following documents:  
EN IEC 60079-0:2018      EN IEC 60079-7:2015+A1:2018      EN 60079-18:2015+A1:2017  
IEC 60079-31:2022 Ed. 3

- 10 The equipment shall be marked with the following:



Ex eb mb IIC T4 Gb

Ex tb IIIC T118°C Db

Ta= -40°C to +55°C or

Ta= -40°C to +40°C when the optional protective cover is fitted.



CML 21UKEX3645X  
Issue 0

## 11 Description

The Wolf LED Floodlite comprises a two-part aluminium body with clear glass panel in the front cover, which is available in two sizes –the WF300xxx and the WF250xxx. The front cover is secured to the base unit via four M5 screws. The luminaire is intended for use in temporary or fixed installations and is provided with appropriate mounting brackets for this purpose. Certified Increased Safety terminals, which provide connection facilities for incoming cables and internal wiring connections, are fitted to a retention bracket. One or two encapsulated driver modules are mounted on the retention bracket that is secured to the rear enclosure via two M5 screws. Each module powers an LED array mounted in the base unit. The LED array comprises 18 LEDs, each LED has an optic fitted over it and the complete assembly is encapsulated. Within the luminaire range there is a choice of optics giving different beam/illumination patterns. Internal and external earthing facilities are provided and up to two cable entry holes are provided depending on customer requirements. Increased Safety/Dustproof certified glands or blanking plugs are used in conjunction with the cable entry holes. LV versions are certified between 0 to 50 V ac/dc and operate between 18V or 19V to 50 V. HV versions are certified between 0 to 264 V ac/dc. Within the luminaire range linkable products can be specified which allow for numerous luminaires to be interlinked so power is fed from one point to multiple luminaires in a string configuration. The luminaire is certified for use with approved, sacrificial accessories.

## 12 Certificate history and evaluation reports

Issue	Date	Associated report	Notes
0	06 May 2022	R14154A/00	Issue of the prime certificate.

Note: Drawings that describe the equipment are listed or referred to in the Annex.

## 13 Conditions of Manufacture

The following conditions are required of the manufacturing process for compliance with the certification.

- i. Where the product incorporates certified parts or safety critical components the manufacturer shall ensure that any changes to those parts or components do not affect the compliance of the certified product that is the subject of this certificate.
- ii. At the conclusion of manufacture, and before shipping, each encapsulated LED Array, LV Driver, and HV driver shall be subject to a routine visual inspection to ensure no damage of the encapsulant is evident, such as cracks in the compound, exposure of the encapsulated parts, flaking, inadmissible shrinkage, swelling, decomposition, failure of adhesion, or softening.
- iii. At the conclusion of manufacture, and before shipping, each encapsulated LV driver shall be subject to a routine dielectric strength test of 500 Vac rms, for a period of 60 seconds, without breakdown between the potting compound surface and the enclosure, alternatively a test at 1.2 times the test voltage may be applied for at least 100 ms. The test is also permitted to be conducted at a dc voltage of 140% of the specified ac rms test voltage.
- iv. At the conclusion of manufacture, and before shipping, each encapsulated HV driver shall be subject to a routine dielectric strength test of 1528 Vac rms, for a period of 60 seconds, without breakdown between the potting compound surface and the enclosure, alternatively a test at 1.2 times



**CML 21UKEX3645X  
Issue 0**

the test voltage may be applied for at least 100ms. The test is also permitted to be conducted at a dc voltage of 140% of the specified ac rms test voltage.

v. At the conclusion of manufacture, and before shipping, each encapsulated LED Array shall be subject to a routine dielectric strength test of 700 Vdc, for a period of 60seconds, without breakdown between the positive solder pad of the folded PCB and the surface of the potting compound directly above the positive solder pad. Alternatively, a test at 1.2 times the test voltage may be applied for at least 100 ms.

vi. The equipment covered by this certificate incorporates component certified terminals; it is therefore the responsibility of the manufacturer to continually monitor the status of the certification associated with these terminals. The manufacturer shall inform CML B.V. of any modifications of the terminals that may impinge upon the explosion safety design of their products.

vii. At the conclusion of manufacture, and before shipping, each set of component certified terminals fitted into the HV luminaires shall be subject to a routine dielectric strength test of 1528 Vac rms, for a period of 60 seconds, without breakdown between the un-insulated live parts and the enclosure. Alternatively, a test at 1.2 times the test voltage may be applied for at least 100 ms. The test is also permitted to be conducted at a dc voltage of 140% of the specified ac rms test voltage.

viii. Where the manufacturer fits cable entry devices, the manufacturer shall fit suitably ATEX equipment certified cable entry devices, marked Ex eb IIC and Ex tb IIIC Db. The cable entry devices shall maintain the degree of ingress protection IP64/67 and be suitable for an upper temperature of at least 75°C, as well as the lower ambient.

ix. At the conclusion of manufacture, and before shipping, each set of component certified terminals fitted into the LV luminaires shall be subject to a routine dielectric strength test of 500 Vac rms, for a period of 60 seconds, without breakdown between the un-insulated live parts and the enclosure. Alternatively, a test at 1.2 times the test voltage may be applied for at least 100 ms. The test is also permitted to be conducted at a dc voltage of 140% of the specified ac rms test voltage

#### **14 Specific Conditions of Use**

The following conditions relate to safe installation and/or use of the equipment.

i. The enclosures paint coated surface may be non-conducting and may generate an ignition-capable level of electrostatic charge under certain extreme conditions within a dust atmosphere. The user shall ensure that the equipment shall not be used in a location where the external conditions are conducive to the build-up of electrostatic charge on non-conductive surfaces. Additionally, the equipment shall only be cleaned with a damp cloth.

ii. The equipment is certified for use with an approved range of accessories that are designed to protect the product and must be supplied by Wolf Safety. Refer to the manufacturer's instructions regarding the replacement frequency of the approved accessories.

iii. Fitting the Protective Cover lowers the maximum ambient temperature from +55°C to +40°C.

## Certificate Annex

**Certificate Number** CML 21UKEX3645X  
**Equipment** WF-300xxx and WF-250xxx LED Floodlite Luminaires  
**Manufacturer** The Wolf Safety Lamp Co. Limited



The following documents describe the equipment defined in this certificate:

### Issue 0

For all drawings, refer to attached certificate CML 18ATEX3372X.